

## SPA-12

### Features :

- 6 MONO channels with combo inputs, switch for LINE/MIC. inputs
- Stereo line inputs: CH7/8, 9/10, 11/12 RCA input
- MIC I: priority
- Phantom power for each MIC. channel
- Input level control, input signal LED
- MONO output, stereo line output, MIC. output for monitoring CH1-CH6 output
- Stereo REC out, RCA output
- Controls: 3 band EQ, master and main level controls
- Switchable AC 220V-240V or DC 24V power supply



### SPA-12

MODEL	SPA-12
S/N Ratio	Microphone : >75dB Line: >90dB
Tone Controls	Bass: $\pm 10$ dB (-100Hz) Treble: $\pm 10$ dB (-10KHz)
Phone Output	0.5W into 47 $\Omega$
Monitor Output	1W RMS
Line Out	1.0V
Power Supply	115/230Vac, 60/50Hz / 12W; 24DC, 0.45A
T.H.D.	$\leq 0.01\%$ at 1KHz
Weight (Approx.)	2.9 kg (6.63 lb)